



Schottky Barrier Diode in SOD-123

Features

- High Conductance
- Low forward voltage drop
- Guard Ring Construction for Transient Protection



Mechanical Data

- **Case:** SOD-123 (plastic package). Lead free; RoHS compliant; Halogen free
- **Molding Compound Flammability Rating:** UL 94 V-0
- **Terminals:** High temperature soldering guaranteed: 260 °C/10 sec. at terminals

Applications

- Low Voltage Rectification
- Switch Mode Power Supply
- Inverse Polarity Protection
- High Efficiency DC/DC Conversion
- Low Power Consumption Applications

Absolute Maximum Ratings

Ratings at 25 °C, ambient temperature unless otherwise specified


Parameter	Symbol	MBR0520	MBR0530	MBR0540	MBR0560	MBR0580	Unit
Maximum recurrent peak reverse voltage Maximum RMS voltage	V_{RRM}	20	30	40	60	80	V
	V_{RMS}	14	21	28	42	56	
Mean rectifying current	I_O	0.5					A
Non-repetitive Peak forward surge current @t=8.3ms	I_{FSM}	5.5					A
Power Dissipation	P_d	410					mW
Thermal Resistance Junction to Ambient	$R_{\theta JA}$	244					°C/W
Junction temperature	T_j	125					°C
Storage temperature	T_{stg}	-55~+150					°C

Electrical Characteristics


($T_A = 25\text{ °C}$ unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
Forward voltage	V_F	$I_F=500\text{mA}$			0.45	V
MBR0520					0.55	
MBR0530					0.55	
MBR0540					0.70	
MBR0560					0.80	
Reverse current	I_R	$V_R=20\text{V}$ $V_R=30\text{V}$ $V_R=40\text{V}$ $V_R=60\text{V}$ $V_R=80\text{V}$			80	μA
MBR0520						
MBR0530						
MBR0540						
MBR0560						
Capacitance between terminals	C_T	$V_R=4\text{V}, f=1\text{MHz}$		30		pF


Typical Characteristics ($T_{amb} = 25\text{ }^{\circ}\text{C}$ unless otherwise specified)




Package Dimensions



Pad Dimensions



Package Dimensions



Ordering information

Order code	Package	Packaging option	Base quantity	Packaging specification
MBR05x0	SOD-123	Tape and reel	3000pcs / reel	EIA STD RS-481

Revision history

Date	Revision	Changes
23-May-2012	1.0	Initial release

CAUTION / WARNING

Information in this document is believed to be accurate and reliable. However, CREATEK does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

Users should independently evaluate the suitability of and test each product selected for their own applications, and CREATEK assumes no liability whatsoever relating to the choice, selection or use of the CREATEK products and services described herein.

CREATEK reserves the right to change or update, without notice, any information contained in this publication; to change, without notice, the design, construction, processing, or specification of any product; and to discontinue or limit production or distribution of any product.

Information in this document supersedes and replaces all information previously supplied.

Products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of an CREATEK product can reasonably be expected to result in personal injury, death or severe property or environmental damage. CREATEK accepts no liability for inclusion and/or use of CREATEK products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.


This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from national authorities.

Resale of CREATEK products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by CREATEK for the CREATEK product or service described herein and shall not create or extend in any manner whatsoever, any liability of CREATEK.

CREATEK expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. CREATEK only obligations are those in the CREATEK Standard Terms and Conditions of Sale and in no case will CREATEK be liable for any incidental, indirect, or consequential damages arising from the sale, resale, use, or misuse of its products.

Specifications are subject to change without notice

© Copyright 2009, CREATEK Microelectronics

 CREATEK® is a registered trademark of CREATEK Microelectronics

All rights reserved